



Handheld Digital Multimeter

It is a handheld and compact digital multimeter with 3 1/2 digits, full function and high performance for measuring DCV, ACV, DCA, resistance, temperature, frequency, diode, and continuity test. Please read the safety information and warning in this manual carefully, and strictly abide by it.



Basic Function	Range	Basic Accuracy		
		VC 202	VC 38D	VC 203
DC Voltage	200mV/2V/20V/200V	$\pm(0.5\%+2)$	$\pm(0.5\%+2)$	$\pm(0.5\%+2)$
	500V	$\pm(0.8\%+2)$	$\pm(0.8\%+2)$	$\pm(0.8\%+2)$
AC Voltage	200V/500V	$\pm(1.2\%+10)$	$\pm(1.2\%+10)$	$\pm(1.2\%+10)$
Dc Current	200uA			
	2mA/20mA	$\pm(1.0\%+2)$	$\pm(1.0\%+2)$	$\pm(1.0\%+2)$
	200mA	$\pm(1.2\%+2)$	$\pm(1.2\%+2)$	$\pm(1.2\%+2)$
	10A	$\pm(2.0\%+5)$	$\pm(2.0\%+5)$	$\pm(2.0\%+5)$
Resistance	200Ω	$\pm(0.8\%+5)$	$\pm(0.8\%+5)$	$\pm(0.8\%+5)$
	2kΩ/20kΩ/200kΩ	$\pm(0.8\%+2)$	$\pm(0.8\%+2)$	$\pm(0.8\%+2)$
	20MΩ	$\pm(1.0\%+5)$	$\pm(1.0\%+5)$	$\pm(1.0\%+5)$
	200MΩ	$\pm(5.0\%+20)$	$\pm(5.0\%+20)$	
				$\pm(1.0\%+3)$
				$\pm(1.0\%+4)$
Spection Function				
Diode test		V	V	V
Backlight		V	V	V
Data hold		V	V	V
Continuity		V	V	V
200mA protection		V	V	V
Square Wave output		V	V	
Celsius & Fahrenheit				V
Battery measurement				