

## Portable Digital Clamp Multimeter VC6016B+

The 6000counts is a pocket-sized 3 5/6-digit RMS auto-scanning digital meter that does not require a dial to select a function. The meter will automatically recognize and measure based on the input voltage/ current/resistance/current. It has stable performance, high precision, high reliability, clear reading and overload protection. Driven by AAA 1.5V battery, the instrument adopts large screen LCD display and adopts boost power supply. Even at the edge of 2.3V low battery, it can ensure the high brightness of backlight and flashlight. The meter is easy to carry and is very popular among users. The instrument's backlight can be turned on and off automatically after 15 seconds. This series of instruments can be used to measure DC voltage and AC voltage, AC current 600A, resistance, capacitance, diode, temperature, continuity test, square wave output, frequency measurement and true RMS. It is a superior tool and an ideal tool for laboratories, factories, radio enthusiasts and families.



and families.		
Basic Function	Range	Accuracy
		606G
DCV	6V/60V/600V/1000V	±(0.5%+3)
ACV	5V/60V/600V/750V	±(0.5%+5)
Resistance	600Q/6k/60k/600k/6M/40M(606Gy60M(606H)	±(0.8%+3)
Capacitance	60nF/600nF/6uF/600uF/6mF/30mF	±(2.0%+8)
Frequency	10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz	±(0.01%+2)
DCA	6A/60A/600A	±(3%+30)
Temperature	(-2-1300)°C(44~1832)°F	V
Operation Way		Auto Range
Max. Display		5999
True RMS		V
Diode Test		V
Continuity Buzzer		V
Back Light		V
Square Wave Output		V
NCV Measurement		V
Flashlight Lighting		V
Battery		2 * 1.5V
LCD Size		32*22mm
Product Color		Orange and Black
Product Net Weight		176g
Product Size		174*66*30mm
Clamp Size		25mm
Standard Accessories		Instruction Manual, Bag,Test Leads, Probe (only for
Standard Inner Pack- ing		Color Box
Carton Size		45'42'27cm
Standard Quantity Per Carton		60pcs
Standard Gross Weight		23.6KG