

VICTOR[®]

Mini Palm Digital Multimeter VC921

This mini professional multi-functional multimeter with stable performance and high precision can measure DC/AC voltage, resistance, capacitance, frequency and duty ratio. It also can test diode and continuity. With dual-integral A/D converter, this excellent tool is great for lab, factory and family.



Basic Function	Range	Basic accuracy
DC Voltage	400m/4/40/400/600V	±(0.5%+4)
AC Voltage	400m/4/40/400/600V	±(0.8%+6)
Resistance	400Ω/4kΩ/40kΩ/400kΩ/ 4MΩ/40MΩ	±(0.8%+4)
Capacitance	4n/40n/400n/4u/ 40u/2000uF	±(3.5%+8)
Frequency	100Hz/1000Hz/10kHz/ 100kHz/1MHz/10MHz	±(0.5%+4)
Special Function		
Diode test		V
Continuity buzzer		V
Low battery indication		V
Data Hold		V
Auto power off		V
Max. value measurement		V
Shock proof protection		V
Frequency		V
Duty cycle measuring		V
Input impedance		10MΩ
Sampling rate		3 times/s
AC Frequency response		40-400Hz
Operation way		Auto range
Max. Display		3999
LCD size		55x43mm
Battery		3V (1.5x2)
Product Net Weight		Approx:180
Product Dimension		145x80x28mm
Standard Accessories		Test leads, battery, instruction manual
Standard inner packing		Color box
Standard Quantity Per Carton		64Pcs
Carton size		290x255x390mm
Standard Gross Weight		Approx:10kg